

Features:

1. Two SIM cards in one iPhone, single standby
2. Auto-switch between SIM cards
3. Enable to edit switching time
4. Enable to edit display name of SIM which can be showed on iPhone screen.

Installation:


1. Place normal SIM into sim slot



2. Place nano adapter into metal card holder




3. Put nano SIM on the nano adapter




4. Fold the flexible PCB and insert into iPhone



5. Insert into side slot of iPhone



6. Put case on



Instruction:

1. Enter Setting – Phone - SIM Applications, it shows “SIMore” menu:

Switch Number

Switch Number:
Manual switching between SIM-1 to SIM-2
Select SIM-1 to activate SIM-1
Select SIM-2 to activate SIM-2

Short key function:

You can switch between SIMs by dialling the following short codes:
Dial #11 to select SIM-1
Dial #22 to select SIM-2
Dial #99 to pop up SIMore menu.

Set Number

Set Number:
Name SIM-1: Change name for SIM-1
Name SIM-2: Change name for SIM-2
Name SIM cards (SIM1 & SIM2) with number only.
(Default SIM cards name are SIM-1 & SIM-2).
Reset : press to reset SIM's name to default.

Auto/Switch

“Auto/SWITCH” Activation de la permutation automatique ON/OFF .
Switch automaticaly from SIM-1 to SIM-2.
The Auto Switching function is “OFF” by default.
ON: to switch ON the Auto/Switch function
OFF: to Switch OFF the Auto/Switch function
SIM1 Time:
Edit switching time by selecting SIM-1 time:03
SIM2 Time:
Edit switching time by selecting SIM-2 time:03
Default switch time: 3min.
Available switch time: 0 ~99min.
Ex: 75 = 1hour and 15 minutes.

Content:

·Dual SIM Adapter × 1

Notes:

Please restart iPhone if no network's signal after switching.

Warning: the shortcut key function not supported by all mobile phones.

More information on :

WWW.SIMORE.COM