

Features:


1. Two SIM cards in one iPhone, single standby
2. Auto-switch between SIM cards
3. Enable to edit switching time
4. Enable to edit display name of SIM which can be showed on iPhone screen.

Installation:


1. Place normal SIM into sim slot



2. Place Micro adapter into metal card holder




3. Place Micro SIM on the Micro adapter--




4. Fold the flexible PCB and insert into iPhone



5. Insert into side slot of iPhone



6. Put case on



Instruction:

1. Enter Setting – Phone - SIM Applications, it shows “SIMore” menu:

Switch Number

Switch Number:

Manual switching between SIM-1 to SIM-2
Select SIM-1 to activate SIM-1
Select SIM-2 to activate SIM-2

Short key function:

You can switch between SIMs by dialling the following short codes:
Dial #11 to select SIM-1
Dial #22 to select SIM-2
Dial #99 to pop up SIMore menu.

Set Number

Set Number:

Name SIM-1: Change name for SIM-1
Name SIM-2: Change name for SIM-2
Name SIM cards (SIM1 & SIM2) with number only.
(Default SIM cards name are SIM-1 & SIM-2).
Reset : press to reset SIM's name to default.

Auto/Switch

“Auto/SWITCH” Activation de la permutation automatique ON/OFF .

Switch automaticaly from SIM-1 to SIM-2.

The Auto Switching function is “OFF” by default.

ON: to switch ON the Auto/Switch function

OFF: to Switch OFF the Auto/Switch function

SIM1 Time:

Edit switching time by selecting SIM-1 time:03

SIM2 Time:

Edit switching time by selecting SIM-2 time:03

Default switch time: 3min.

Available switch time: 0 ~99min.

Ex: 75 = 1hour and 15 minutes.

Content:

·Dual SIM Adapter × 1

Notes:

Please restart iPhone if no network's signal after switching.

Warning: the shortcut key function not supported by all mobile phones.

More information on :

WWW.SIMORE.COM