



- 1 Take the cutting sticker provided in the kit and your SIM cards.
- 2 Fix the cutting sticker guide on your SIM card respecting the bevel position.
- 3 Using scissors, cut the SIM card by precisely following the interior edge of the cutting marks.
Remove the cutting sticker and renew the operation for the second SIM card.
- 4 Check the cutting of your SIM cards by placing them on the white stencils provided in your kit.
Place the recovery sticker on the back of it and cut away the unnecessary parts.
- 5 Test the cut out of your SIM cards by inserting them individually into your mobile.
- 6 Remove the Simore's protective sheet.
- 7 Place your two cut SIM cards in both SIM-1 & SIM-2 in the provided places in the Simore.
- 8 Gently squeeze only the outer edges of your Simore.
NEVER PRESS ON THE 12 METAL CONTACT POINTS OF THE SIMORE.
By using the pen of a smart phone, perfectly smooth contours of your Simore, to ensure the connection between your SIM cards and Simore before the installation in your mobile phone.
- 9 Insert the Simore into your mobile "SIM card" slot.
Replace your battery and close the mobile phone cover.
It's ready, you can switch on your mobile phone.

- Steps 10 - 11 and 12 are optional. Please use the protective sticker only if you encounter contact problems between the SIM cards and the Simore device.
We recommend not to use the protective seal in phones with a very thin or small SIM card location.
- 10 Take the protection sticker provided in the kit.
 - 11 Fix the protection sticker on the compiled Simore with the two SIM cards and respect the markings.
 - 12 Fold back the three sides of the sticker around the Simore.